



Mixer Amplifier

Features:

Controls

- Front: 3 Channel Volume Control & Tone Control,
- Master Volume Rear: Line/MIC selector, Talk over selector and level volume,
- Phantom Switch

Connectors

- Euro Block with Electronically Balanced for Channel 1-3 Input
- XLR, PHONE, RCA Jack for Channel 1-3 Input
- Screw terminal for Speaker Output

VOX control with ducking level potentiometer.

Media Player

- FM radio, Bluetooth, USB memory stick interface, AUX IN & IR Remote control
- With TFT control screen
- Indicators: Power, Signal, -10dB, Clip and Protect

Protection: Output Current Limiting, Thermal Protection & DC Offset Protection

Cooling: Convection Cooling



Model	JMA - 1120
Rated Power (RMS)	120W
Input sensitivity / Impedance	MIC: -36dB / 600Ω Balanced Line: - 6dB / 10 k Ω Unbalanced 100V(83 Ω),70V(41Ω), 4Ω,8Ω 50Hz - 18kHz
Output level / Impedance	<1%
Frequency Response (-3dB)	>80dB
T.H.D (1kHz, Rated Power)	100Hz, 10kHz ±10dB AC 100-240 V. 50/60Hz
Signal to Noise Ratio	5.5 kg
Tone Control	280 x 60 x 200mm
Power Source	120W
Weight (Net)	MIC: -36dB / 600Ω Balanced Line: - 6dB / 10 k Ω Unbalanced 100V(83 Ω),70V(41Ω), 4Ω,8Ω 50Hz - 18kHz
Dimensions (W x H x D)	<1%
Media player	
Frequency Range (FM)	87.5-108.0 MHz
Channel step (FM)	50kHz
Sensitivity (FM)	2 uV at 30dB S/N FM: >60 dB
Signal to noise ratio	MP3: >80 dbs.



Legende Integrated Industries

25 Mohamed El Nady St, 8th District, Nasr City

legende-ind.com

info@legenede.com