



## 6 Zone Mixer Amplifier with Zone volume control

### Features:

#### Controls

- Front : 4 Input Channel Volume Control and 1 selectable source input Volume control,
- Master Volume Control, 6 Zone Speaker Selector with 6 step attenuator.
- Rear: Talk over Switch (VOX) & Phantom Power Switch for Channel 1-4. Chime
- Enable with volume control.
- Bypass contact input & system mute.

#### Connectors

- Input: Channel 1 - 4: Electronically Balanced with chime switch.
- Aux: Dual RCA.
- Remote Mic: RJ45.
- Emergency Alarm input: Euro block.
- Output: Speaker Output: Euro Block. Attenuated and Switched 6 CH, Direct
- Output 4Ω, 8Ω, 70V, 100V.
- REC Out & Link out: RCA.
- Contact: Ext. Chime: Euro block.
- MUTE: Euro block.

Media player module: FM Tuner / Recordable MP3 / Bluetooth player.

Indicators: SIG, -10dB, CLIP & Protect. Zone selector.

Protection: Output Current Limiting, Thermal Protection & DC Offset Protection.

Cooling: Convection Cooling.

Option: Rack Mount Kit



Mplayer A



Mplayer B



Mplayer C



3 types of Media Player for you to choose to add to the Amplifier

Model		JMA-6130	JMA-6240	JMA-6360		
Rated Power (RMS)		130W	130W	130W		
Input sensitivity / Impedance		Channel 1-4				
		-36dB / -10dB Selectable / 20 kΩ Balanced				
		Aux				
		0dB / 20 kΩ Balanced				
		Remote Mic				
		0dB / 20 kΩ Balanced				
Output level / Impedance		Speaker Output	Hi-z	100V (83Ω), 70V (42Ω)	100V (42Ω), 70V (21Ω)	100V (28Ω), 70V (14Ω)
			Low-z	31V (8Ω), 22V (4Ω)	44V (8Ω), 31V (4Ω)	54V (8Ω), 38V (4Ω)
		Rec Out		0dB / 600Ω Unbalanced		
		Link Out		0dB / 600Ω Unbalanced		
Frequency Response (-3dB)		65Hz - 18kHz				
T.H.D (1kHz, Rated Power)		<1%				
Signal to Noise Ratio		>80dB				
Tone Control		± 10dB				
Power Source		100Hz, 10KHz				
		AC 115 / 230 V, 50/60Hz				
Weight (Net)		9 kg	10 kg	11 kg		
Dimensions (WxHxD)		420 x88 x 320mm				



Legende Integrated Industries  
25 Mohamed El Nady St, 8th District, Nasr City

legende-ind.com  
info@legenede.com